



# Falcon Fires

**Real Gas Fuel Effect Fires**

[www.falconfires.com](http://www.falconfires.com)

## **Introduction.**

### **72LS10CE Li-ion Battery Charger System**

72LS10CE is a plug-in 7.2V Li-ion battery charger system.

**Rechargeable Battery Option On all appliances using a 7.2 volt battery as a energy source,**

The 7.2V lithium battery system previously fitted into many gas appliances had an expected life span, given normal usage, of approximately one year until you as the end user would either arrange to replace the battery or indeed “do it yourself”.

We have developed a rechargeable unit that has the ability to be retro fitted, on **any** existing 7.2V Battery operated remote controlled gas Appliance.

## **Technical specification**

Input: 230V~50Hz AC 16W

Output: 7.2V DC 1000mA

## **Warning**

1. For indoor use only.
2. Only use for charging suitable Li-ion batteries.
3. This appliance is not intended for use by persons (including children) with reduced physical, sensory or mental capabilities, or lack of experience and knowledge, unless they have been given supervision or instruction concerning use of the appliance by a person responsible for their safety.
4. Children should be supervised to ensure that they do not play with the appliance.

## Fitting Instructions (Falcon Fires only)



### Other Bracket options are available for other appliances

1. Remove 10mm nut from the front right hand side of the support leg, align socket bracket over stud and tighten into place with 10mm nut.
2. Remove old battery by separating 3 pin plug and socket and connect new plug in the the recently disconnected socket
3. Route wiring and battery under appliance pipe work, taking care not to expose any wiring to the hot underside of the appliance.

### Directions for use

1. Insert the battery charger into the AC outlet (Wall Socket).
2. Insert the battery charger lead into the charging socket. The Red LED light indicates that charging is in progress, fast charging is now in progress.
3. When the battery pack is fully charged, it turns to trickle charge mode, and the indicator turns to green.
4. When the charging process has finished, remove the charger from the wall socket and unplug the lead from the appliance socket.

N.B. The appliance will not operate when charging is in progress.

### Adaco Manufacturing Ltd.

Kilcolgan, Co. Galway

00 353 (0)91 796 788

[info@falconfires.com](mailto:info@falconfires.com)

[www.falconfires.com](http://www.falconfires.com)